

- (f) Generating Units, System Units, Loads and System Resources shall be dispatched during the operating hour only until the next variation in Demand or the end of the operating hour, whichever is sooner. In dispatching such resources, the ISO makes no further commitment as to the duration of their operation, nor the level of their output or Demand, except to the extent that a Dispatch instruction causes Energy to be delivered in a different BEEP Interval.

**2.5.22.3 Ancillary Services Dispatch.** The ISO may dispatch Generating Units, Loads, System Units and System Resources contracted to provide Ancillary Services (either procured through the ISO's competitive market, or self provided by Scheduling Coordinators) to supply Imbalance Energy.

**2.5.22.4** During normal operating conditions, the ISO shall dispatch the following resources to supply Imbalance Energy: (i) those Generating Units, Loads, System Units and System Resources having offered Supplemental Energy bids, (ii) those Generating Units, Loads, System Units and System Resources contracted to provide Replacement Reserve and (iii) those Generating Units, Loads, System Units and System Resources that have contracted to provide Spinning and Non-Spinning Reserve, except for those resources that have indicated that the capacity reserved would be available to supply Imbalance Energy only in the event of the occurrence of an unplanned Outage, a Contingency or an imminent or actual System Emergency. In the event of an unplanned Outage, a Contingency or a threatened or actual System Emergency, the ISO may also dispatch all other Generating Units, Loads, System Units and System Resources contracted to provide Spinning Reserve or Non-Spinning Reserve to supply Imbalance Energy. If a Generating Unit, Load, System Unit or System Resource, which is supplying Operating Reserve, is dispatched to provide

Imbalance Energy, the ISO shall replace the Operating Reserve from the same or another resource within the time frame specified in the WSCC guidelines.

# **Attachment 1**

## **Attachment 2**