 California ISO	Operating Procedure	Procedure No.	4420C
		Version No.	8.1
		Effective Date	8/28/2018
System Emergency Notice Templates		Distribution Restriction: None	

1. Procedure Detail

1.1. Purpose and Distribution

The California ISO sends System Emergency notices when adverse grid or market conditions require activation of the California ISO Electrical Emergency Plan, which is implemented through the System Emergency procedures. Notices are targeted to control centers and communications departments of Participating Transmission Owners, Utility Distribution Companies, Metered Subsystems, Market Participants as well as state, federal, regulatory and oversight agencies. Not all System Emergency notices are necessarily sent to all recipients but rather to the stakeholders for each notice identified by the ISO. Subsequent re-transmissions of these notices by media, public safety agencies, and others extend the audience to a much wider range of recipients than those specified above.


System Emergency notices may be issued on a California ISO Grid or Regional (Northern or Southern California) basis. In addition to the standardized text in the following pages, California ISO Operators can elect to provide additional details and descriptions specific to the event.

1.1.1. Advisories, NOT Dispatch Instructions

System Emergency notices do not serve as, nor should they be mistaken for, dispatch instructions or orders issued by the ISO. They are advisories only and dispatch instructions relative to system emergencies will be issued through established modes.

1.1.2. Disclaimer

System Emergency notices are based on current conditions of the transmission grid system. While an ISO System Emergency notice reflects the most current information available to the ISO at the time of issuance, transmission grid system conditions are subject to sudden and rapid change without warning and the accuracy of any notice cannot be assured. These ISO notices are provided solely for informational purposes. Reliance by any party on the contents of these ISO notices, regardless of any errors, omissions, inaccuracies, and/or subsequent changed conditions shall not be made the basis for any claim, demand, or cause for action against the ISO. Any recipient's decisions or actions that may be based in any way whatsoever on the contents of these ISO notices shall be the sole responsibility of the recipient.

 California ISO	Operating Procedure	Procedure No.	4420C
		Version No.	8.1
		Effective Date	8/28/2018
System Emergency Notice Templates		Distribution Restriction: None	


1.2. Issuance of System Emergency Notices

1.2.1. Alert Notice

ISO Grid, Northern CA Region, Southern CA Region or VEA Region
<p>The California ISO hereby issues a [CAISO Grid, Northern CA Region, Southern CA Region or VEA Region] Alert Notice, effective [Start Date] at [Start Time] through [End Date, End Time].</p> <p>Reason: [Reason]</p> <p>Conservation efforts are encouraged for the time period specified in this notice. Energy Market Participants are encouraged to offer additional Supplemental Energy and Ancillary Service bids.</p> <p>Refer to the ISO System Emergency Fact Sheet (http://www.caiso.com/Documents/SystemAlertsWarningsandEmergenciesFactSheet.pdf) for additional detail.</p> <p>Monitor system conditions on Today's Outlook (http://www.caiso.com/TodaysOutlook/Pages/default.aspx) and check with local electric utilities for additional information.</p> <p>Notice issued at: [Notice Post Date]</p>

1.2.2. Warning Notice

ISO Grid, Northern CA Region, Southern CA Region or VEA Region
<p>The California ISO hereby issues a [CAISO Grid, Northern CA Region, Southern CA Region or VEA Region] Warning Notice, effective [Start Date], [Start Time] through [End Date], [End Time].</p> <p>Reason: [Reason]</p> <p>Conservation efforts are advised for the time period specified in this notice. Energy Market Participants are encouraged to offer additional Supplemental Energy and Ancillary Service bids.</p> <p>In the Warning period, if operating Reserves continue to deplete and a Stage 1 is imminent, the ISO may curtail Interruptible Loads* to prevent escalating to a Stage 1 Emergency.</p>

 California ISO	Operating Procedure	Procedure No. 4420C
		Version No. 8.1
		Effective Date 8/28/2018
System Emergency Notice Templates		Distribution Restriction: None

**ISO Grid,
Northern CA Region,
Southern CA Region or VEA Region**

Refer to the ISO System Emergency Fact Sheet (<http://www.caiso.com/Documents/SystemAlertsWarningsandEmergenciesFactSheet.pdf>) for additional detail.

Monitor system conditions on Today's Outlook (<http://www.caiso.com/TodaysOutlook/Pages/default.aspx>) and check with local electric utilities for additional information.

[Supersedes?]

Notice issued at: [Notice Post Date]

*Interruptible Loads comprise customers from Southern California Edison, San Diego Gas and Electric, and Pacific Gas & Electric who opt for service under "Interruptible Rate Schedules" and "Emergency Curtailment" tariffs authorized by the California Public Utilities Commission that provide for periodic curtailments by the ISO. The ISO will also curtail loads that elect to participate in ISO Load Interruption Programs, described in ISO Operating Procedure [4510 Load Management Programs and Underfrequency Load Shedding](#).

1.2.3. 1-Hour Notification of Probable Load Interruptions


**ISO Grid,
Northern CA Region,
Southern CA Region or VEA Region**

The CAISO anticipates the need to interrupt firm load for the period [Start Date], [Start Time] through [End Date], [End Time] in the amount of [MW amount] MW for each respective hour for the period for [CAISO Grid, Northern CA Region, Southern CA Region or VEA Region] based on system conditions as of [Notice Post Date].

Maximum conservation efforts are encouraged for the time period specified in this notice. Utility Distribution Companies and Metered Subsystems await further orders from the ISO. The ISO will issue a 'Stage 3 Emergency Notice' when the load interruptions have actually begun or are imminent.

Refer to the ISO System Emergency Fact Sheet (<http://www.caiso.com/Documents/SystemAlertsWarningsandEmergenciesFactSheet.pdf>) for additional detail.

Monitor system conditions on Today's Outlook (<http://www.caiso.com/TodaysOutlook/Pages/default.aspx>) and check with local electric utilities for additional information.


 California ISO	Operating Procedure	Procedure No. 4420C
		Version No. 8.1
		Effective Date 8/28/2018
System Emergency Notice Templates		Distribution Restriction: None

1.2.4. Stage 1 Emergency Notice


ISO Grid, Northern CA Region, Southern CA Region or VEA Region
<p>The California ISO hereby issues a [CAISO Grid, Northern CA Region, Southern CA Region or VEA Region] STAGE 1 SYSTEM EMERGENCY Notice, effective [Start Date], [Start Time] through [End Date], [End Time].</p> <p>Reason: [Reason]</p> <p>Refer to the ISO System Emergency Fact Sheet (http://www.caiso.com/Documents/SystemAlertsWarningsandEmergenciesFactSheet.pdf) for additional detail.</p> <p>Operating Reserves are currently, or forecast to be, less than amounts required by the Western Electricity Coordinating Council. If Operating Reserves deplete further, the ISO will declare a Stage 2 System Emergency and may begin curtailing Interruptible Loads*.</p> <p>Monitor system conditions on Today's Outlook (http://www.caiso.com/TodaysOutlook/Pages/default.aspx) and check with local electric utilities for additional information.</p> <p>[Supersedes?]</p> <p>Notice issued at: [Notice Post Date]</p> <p>* Interruptible Loads are comprised of customers from Southern California Edison, San Diego Gas & Electric and Pacific Gas & Electric who opt for service under "Interruptible Rate Schedules" and "Emergency Curtailment" tariffs authorized by the California Public Utilities Commission that provide for periodic curtailments by the California ISO. The ISO will also curtail loads that elect to participate in California ISO Load Interruption Programs, described in Operating Procedure 4510.</p>

1.2.5. Stage 2 Emergency Notice

ISO Grid, Northern CA Region, Southern CA Region or VEA Region
<p>The California ISO hereby issues a [CAISO Grid, Northern CA Region, Southern CA Region or VEA Region] STAGE 2 SYSTEM EMERGENCY Notice effective [Start Date], [Start Time] through [End Date], [End Time].</p> <p>Reason: [Reason]</p>


 California ISO	Operating Procedure	Procedure No. 4420C
		Version No. 8.1
		Effective Date 8/28/2018
System Emergency Notice Templates		Distribution Restriction: None

ISO Grid, Northern CA Region, Southern CA Region or VEA Region
<p>Refer to the ISO System Emergency Fact Sheet (http://www.caiso.com/Documents/SystemAlertsWarningsandEmergenciesFactSheet.pdf) for additional detail.</p> <p>The ISO will be calling on UDC's to implement their Interruptible Loads* and requests maximum conservation. Energy Market Participants are encouraged to offer additional Supplemental Energy and Ancillary Service bids.</p> <p>Non-Spinning Reserve requirement cannot be maintained. If Non-Spinning Reserves deplete further, the ISO will declare a Stage 3 System Emergency and begin curtailing firm loads.</p> <p>Monitor system conditions on Today's Outlook (http://www.caiso.com/TodaysOutlook/Pages/default.aspx) and check with local electric utilities for additional information.</p> <p>[Supersedes?]</p> <p>Notice issued at: [Notice Post Date]</p> <p>* Interruptible Loads are comprised of customers from Southern California Edison, San Diego Gas & Electric and Pacific Gas & Electric who opt for service under "Interruptible Rate Schedules" and "Emergency Curtailment" tariffs authorized by the California Public Utilities Commission that provide for periodic curtailments by the California ISO. The ISO will also curtail loads that elect to participate in California ISO Load Interruption Programs, described in Operating Procedure 4510.</p>

 California ISO	Operating Procedure	Procedure No. 4420C
		Version No. 8.1
		Effective Date 8/28/2018
System Emergency Notice Templates		Distribution Restriction: None

1.2.6. Stage 3 Emergency Notice

ISO Grid, Northern CA Region, Southern CA Region or VEA Region
<p>The California ISO hereby issues a [CA ISO Grid, Northern CA Region, Southern CA Region or VEA Region] Stage 3 System Emergency Notice effective [Start Date], [Start Time] through [End Date], [End Time].</p> <p>Reason: [Reason]</p> <p>Refer to the ISO System Emergency Fact Sheet (http://www.caiso.com/Documents/SystemAlertsWarningsandEmergenciesFactSheet.pdf) for additional detail.</p> <p>The ISO requires load curtailments, use of Interruptible Loads* and requests Out-of-Market (OOM) and Emergency Energy from all available sources. Maximum conservation efforts are requested.</p> <p>Spinning Reserves have depleted or are forecast to deplete to levels below minimum requirements. Load curtailments are required and will continue until such time as sufficient Spinning Reserves are available.</p> <p>Monitor system conditions on Today's Outlook (http://www.caiso.com/TodaysOutlook/Pages/default.aspx) and check with local electric utilities for additional information.</p> <p>[Supersedes?]</p> <p>Notice issued at: [Notice Post Date]</p> <p>* Interruptible Loads are comprised of customers from Southern California Edison, San Diego Gas & Electric and Pacific Gas & Electric who opt for service under "Interruptible Rate Schedules" and "Emergency Curtailment" tariffs authorized by the California Public Utilities Commission that provide for periodic curtailments by the California ISO. The ISO will also curtail loads that elect to participate in California ISO Load Interruption Programs, described in Operating Procedure 4510.</p>


 California ISO	Operating Procedure	Procedure No. 4420C
		Version No. 8.1
		Effective Date 8/28/2018
System Emergency Notice Templates		Distribution Restriction: None

1.2.7. Transmission Emergency Notice

ISO Grid, Northern CA Region, Southern CA Region or VEA Region
<p>The California ISO hereby issues a [CA ISO Grid, Northern CA Region, Southern CA Region or VEA Region] TRANSMISSION EMERGENCY Notice effective [Start Date], [Start Time] through [End Date], [End Time] based on conditions as of [Notice Post Date].</p> <p>Reason: [Reason]</p> <p>Refer to the ISO System Emergency Fact Sheet (http://www.caiso.com/Documents/SystemAlertsWarningsandEmergenciesFactSheet.pdf) for additional detail.</p> <p>Monitor system conditions on Today's Outlook (http://www.caiso.com/TodaysOutlook/Pages/default.aspx) and check with local electric utilities for additional information.</p> <p>[Supersedes?]</p> <p>Notice issued at: [Notice Post Date]</p>

1.2.8. Firm Load Interruption - Transmission Emergency Notice

ISO Grid, or Specific Area
<p>As of [Start Time] the California ISO has requested [Number/Value] MW of load to be shed in [Area] due to a transmission emergency. A separate notification will be made when load has been restored.</p> <p>Refer to the ISO System Emergency Fact Sheet (http://www.caiso.com/Documents/SystemAlertsWarningsandEmergenciesFactSheet.pdf) for additional detail.</p> <p>Monitor system conditions on Today's Outlook (http://www.caiso.com/TodaysOutlook/Pages/default.aspx) and check with local electric utilities for additional information.</p> <p>Notice issued at: [Notice Post Date]</p>


 California ISO	Operating Procedure	Procedure No. 4420C
		Version No. 8.1
		Effective Date 8/28/2018
System Emergency Notice Templates		Distribution Restriction: None

1.2.9. Firm Load Interruption – Stage 3 Emergency Notice

ISO Grid, or Specific Area
<p>As of [Start Time] the California ISO has requested [Number/Value] MW of load to be shed due to the Stage 3 Emergency. A separate notification will be made when load has been restored.</p> <p>Refer to the ISO System Emergency Fact Sheet (http://www.caiso.com/Documents/SystemAlertsWarningsandEmergenciesFactSheet.pdf) for additional detail.</p> <p>Monitor system conditions on Today's Outlook (http://www.caiso.com/TodaysOutlook/Pages/default.aspx) and check with local electric utilities for additional information.</p> <p>Notice issued at: [Notice Post Date]</p>


1.2.10. Restricted Maintenance Operations Notice

ISO Grid, Northern CA Region, Southern CA Region, or VEA Region
<p>The California ISO is declaring a [CA ISO Grid, Northern CA Region, Southern CA Region or VEA Region] RESTRICTED MAINTENANCE OPERATIONS Notice from [Start Date], [Start Time] through [End Date], [End Time].</p> <p>Reason: [The ISO is anticipating high loads and temperatures across the CAISO Grid, Northern CA Region, Southern CA Region or VEA Region].</p> <p>Refer to the ISO System Emergency Fact Sheet (http://www.caiso.com/Documents/SystemAlertsWarningsandEmergenciesFactSheet.pdf) for additional detail.</p> <p>Market Participants are cautioned to avoid actions, which may jeopardize generator and/or transmission availability.</p> <p>Monitor system conditions on Today's Outlook (http://www.caiso.com/TodaysOutlook/Pages/default.aspx) and check with local electric utilities for additional information.</p> <p>Supersedes: []</p> <p>Notice issued at: [Notice Post Date]</p>

 California ISO	Operating Procedure	Procedure No.	4420C
		Version No.	8.1
		Effective Date	8/28/2018
System Emergency Notice Templates		Distribution Restriction: None	


1.2.11. Northern CA Region Restricted Maintenance Operations – Gas Supply Insufficiency

ISO Grid, Northern CA Region
<p>The California ISO is declaring a Northern CA Region RESTRICTED MAINTENANCE OPERATIONS Notice from [Start Date], [Start Time] through [End Date], [End Time].</p> <p>Reason: [Natural gas curtailments in the Northern California area].</p> <p>Restricted Maintenance Operations, as detailed in ISO Operating Procedure 4120, Gas Transmission Pipeline Derates or Outages, will be in effect. Outages are not being Canceled at this time but need to follow the scheduled times to avoid cancellation. If outages need to be Canceled, a separate RMO notice will be issued with additional information.</p> <p>Market Participants are cautioned to avoid actions, which may jeopardize generator and/or transmission availability.</p> <p>Refer to the ISO System Emergency Fact Sheet (http://www.caiso.com/Documents/SystemAlertsWarningsandEmergenciesFactSheet.pdf) for additional detail.</p> <p>Monitor system conditions on Today's Outlook (http://www.caiso.com/TodaysOutlook/Pages/default.aspx) and check with local electric utilities for additional information.</p> <p>Supersedes: []</p> <p>Notice issued at: [Notice Post Date]</p>

 California ISO	Operating Procedure	Procedure No. 4420C
		Version No. 8.1
		Effective Date 8/28/2018
System Emergency Notice Templates		Distribution Restriction: None

1.2.12. Southern CA Region Restricted Maintenance Operations – Gas Supply Insufficiency

ISO Grid, Southern CA Region, or VEA Region
<p>The California ISO is declaring a Southern CA Region RESTRICTED MAINTENANCE OPERATIONS Notice from [Start Date], [Start Time] through [End Date], [End Time].</p> <p>Reason: [Natural gas curtailments in the Southern California area].</p> <p>Refer to the ISO System Emergency Fact Sheet (http://www.caiso.com/Documents/SystemAlertsWarningsandEmergenciesFactSheet.pdf) for additional detail.</p> <p>Restricted Maintenance Operations, as detailed in ISO Operating Procedure 4120, Gas Transmission Pipeline Derates or Outages, will be in effect. Outages are not being Canceled at this time but need to follow the scheduled times to avoid cancellation. If outages need to be Canceled, a separate RMO notice will be issued with additional information.</p> <p>The California ISO will be using a gas nomogram in the Day Ahead & Real-Time markets, along with approved outages, for the identified regions based on gas burn limits from the gas companies.</p> <p>Transmission and generation operators are cautioned to avoid actions, which may jeopardize generator and/or transmission availability.</p> <p>Monitor system conditions on Today's Outlook (http://www.caiso.com/TodaysOutlook/Pages/default.aspx) and check with local electric utilities for additional information.</p> <p>Supersedes: []</p> <p>Notice issued at: [Notice Post Date]</p>


 California ISO	Operating Procedure	Procedure No. 4420C
		Version No. 8.1
		Effective Date 8/28/2018
System Emergency Notice Templates		Distribution Restriction: None

1.2.13. Generation Restricted Maintenance Operations Notice

ISO Grid, Northern CA Region, Southern CA Region, or VEA Region
<p>The California ISO is declaring a [CAISO Grid, Northern CA Region, Southern CA Region or VEA Region] GENERATION Restricted Maintenance Operations Notice from [Start Date], [Start Time] through [End Date], [End Time].</p> <p>Reason: [The California ISO anticipates generation resources may be inadequate for the period covered by this notice].</p> <p>Refer to the ISO System Emergency Fact Sheet (http://www.caiso.com/Documents/SystemAlertsWarningsandEmergenciesFactSheet.pdf) for additional detail.</p> <p>Restricted Maintenance Operations, as detailed in ISO Operating Procedure 4420, will be in effect. Additionally, Market Participants are cautioned to avoid actions which may jeopardize generator availability.</p> <p>This notice does not restrict scheduled outages which do not affect generating resource availability.</p> <p>Monitor system conditions on Today's Outlook (http://www.caiso.com/TodaysOutlook/Pages/default.aspx) and check with local electric utilities for additional information.</p> <p>Supersedes: []</p> <p>Notice issued at: [Notice Post Date]</p>

1.2.14. Flex Alert

ISO Grid, Northern CA Region, Southern CA Region, or VEA Region
<p>The California ISO has issued a Flex Alert for [Insert impacted area] effective [Date].</p> <p>Californians are urged to conserve electricity from [Date] at [Time] to [Date] at [Time] to avoid power disruptions.</p> <p>A news release is [pending / has been issued]. The ISO media hotline is (888)516-NEWS.</p> <p>Notice issued at: [Notice Post Date]</p>

 California ISO	Operating Procedure	Procedure No. 4420C
		Version No. 8.1
		Effective Date 8/28/2018
System Emergency Notice Templates		Distribution Restriction: None


1.3. Termination of System Emergency Notices

1.3.1. Alert Cancellation Notice

ISO Grid, Northern CA Region, Southern CA Region, or VEA Region
<p>Effective [Date] at [Time] the California ISO terminates the [ISO Grid, Northern CA Region, Southern CA Region or VEA Region] SYSTEM ALERT in effect since [Effective Date].</p> <p>Refer to the ISO System Emergency Fact Sheet (http://www.caiso.com/Documents/SystemAlertsWarningsandEmergenciesFactSheet.pdf) for additional detail.</p> <p>Monitor system conditions on the California ISO Website at www.caiso.com and check with local electric utilities for additional information.</p> <p>[Supersedes?]</p> <p>Notice issued at: [Notice Post Date]</p>

1.3.2. Warning Cancellation Notice

ISO Grid, Northern CA Region, Southern CA Region, or VEA Region
<p>Effective [Date] at [Time] the California ISO terminates the [ISO Grid, Northern CA Region, Southern CA Region or VEA Region] WARNING in effect since [Effective Date].</p> <p>Refer to the ISO System Emergency Fact Sheet (http://www.caiso.com/Documents/SystemAlertsWarningsandEmergenciesFactSheet.pdf) for additional detail.</p> <p>Monitor system conditions on the ISO Website at www.caiso.com and check with local electric utilities for additional information.</p> <p>[Supersedes?]</p> <p>Notice issued at: [Notice Post Date]</p>


 California ISO	Operating Procedure	Procedure No. 4420C
		Version No. 8.1
		Effective Date 8/28/2018
System Emergency Notice Templates		Distribution Restriction: None

1.3.3. Stage 1 Cancellation Notice

ISO Grid, Northern CA Region, Southern CA Region, or VEA Region
<p>Effective [Date] at [Time] the California ISO terminates the [ISO Grid, Northern CA Region, Southern CA Region or VEA Region] STAGE 1 ELECTRICAL EMERGENCY in effect since [Effective Date].</p> <p>Refer to the ISO System Emergency Fact Sheet (http://www.caiso.com/Documents/SystemAlertsWarningsandEmergenciesFactSheet.pdf) for additional detail.</p> <p>Monitor system conditions on the California ISO Website at www.caiso.com and check with local electric utilities for additional information.</p> <p>[Supersedes?]</p> <p>Notice issued at: [Notice Post Date]</p>

1.3.4. Stage 2 Cancellation Notice

ISO Grid, Northern CA Region, Southern CA Region, or VEA Region
<p>Effective [Date] at [Time] the California ISO terminates the [ISO Grid, Northern CA Region, Southern CA Region or VEA Region] STAGE 2 ELECTRICAL EMERGENCY in effect since [Effective Date].</p> <p>Refer to the ISO System Emergency Fact Sheet (http://www.caiso.com/Documents/SystemAlertsWarningsandEmergenciesFactSheet.pdf) for additional detail.</p> <p>Monitor system conditions on the ISO Website at www.caiso.com and check with local electric utilities for additional information.</p> <p>[Supersedes?]</p> <p>Notice issued at: [Notice Post Date]</p>


 California ISO	Operating Procedure	Procedure No. 4420C
		Version No. 8.1
		Effective Date 8/28/2018
System Emergency Notice Templates		Distribution Restriction: None

1.3.5. Stage 3 Cancellation Notice

ISO Grid, Northern CA Region, Southern CA Region, or VEA Region
<p>Effective [Date] at [Time] the California ISO terminates the [CAISO Grid, Northern CA Region, Southern CA Region or VEA Region] STAGE 3 ELECTRICAL EMERGENCY in effect since [Effective Date].</p> <p>Refer to the ISO System Emergency Fact Sheet (http://www.caiso.com/Documents/SystemAlertsWarningsandEmergenciesFactSheet.pdf) for additional detail.</p> <p>Monitor system conditions on the ISO Website at www.caiso.com and check with local electric utilities for additional information.</p> <p>[Supersedes?]</p> <p>Notice issued at: [Notice Post Date]</p>

1.3.6. Cancel Transmission Emergency Notice

ISO Grid, Northern CA Region, Southern CA Region, or VEA Region
<p>Effective [End Date] at [End Time] the California ISO terminates [CAISO Grid, Northern CA Region, Southern CA Region or VEA Region] TRANSMISSION EMERGENCY in effect since [Effective Date].</p> <p>Refer to the ISO System Emergency Fact Sheet (http://www.caiso.com/Documents/SystemAlertsWarningsandEmergenciesFactSheet.pdf) for additional detail.</p> <p>Monitor system conditions on the ISO Website at www.caiso.com and check with local electric utilities for additional information.</p> <p>[Supersedes?]</p> <p>Notice issued at: [Notice Post Date]</p>

 California ISO	Operating Procedure	Procedure No.	4420C
		Version No.	8.1
		Effective Date	8/28/2018
System Emergency Notice Templates		Distribution Restriction: None	

1.3.7. Flex Alert Cancellation


ISO Grid, Northern CA Region, Southern CA Region, or VEA Region
<p>The California ISO has terminated the Flex Alert issued for [Insert impacted area] on [Date].</p> <p>Thank you for your participation.</p> <p>Notice issued at: [Notice Post Date]</p>

1.3.8. Firm Load Interruptions - Transmission Emergency Cancellation

ISO Grid, Northern CA Region, Southern CA Region, or VEA Region
<p>As of [End Date] at [End time] the California ISO has cancelled the request to shed load due to the Transmission Emergency. Load has been restored.</p> <p>Notice issued at: [Notice Post Date]</p>

1.3.9. Firm Load Interruptions – Stage 3 Emergency Cancellation

ISO Grid, Northern CA Region, Southern CA Region, or VEA Region
<p>As of XX:XX the California ISO has cancelled the request to shed load due to the Stage 3 Emergency. Load has been restored.</p> <p>Notice issued at: [Notice Post Date]</p>

 California ISO	Operating Procedure	Procedure No.	4420C
		Version No.	8.1
		Effective Date	8/28/2018
System Emergency Notice Templates		Distribution Restriction: None	

2. Supporting Information

Operationally Affected Parties

Shared with Public and Peak RC.

References

Resources studied in the development of this procedure and that may have an effect upon some steps taken herein include but are not limited to:


CAISO Tariff	
ISO Operating Procedure	4420 System Emergency 4510 Load Management Programs and Underfrequency Load Shedding
NERC Requirements	
WECC Criterion	
Other References	

Definitions

Unless the context otherwise indicates, any word or expression defined in the Master Definitions Supplement to the CAISO Tariff shall have that meaning when capitalized in this Operating Procedure.

The following additional terms are capitalized in this Operating Procedure when used as defined below:

None.

 California ISO	Operating Procedure	Procedure No.	4420C
		Version No.	8.1
		Effective Date	8/28/2018
System Emergency Notice Templates		Distribution Restriction: None	

Version History

Version	Change	Date
7.5	Modified the sections for Stage 2 and 3 emergencies. Added Version History and a Technical Review Section.	7/16/2014
8.1	Annual Review: <ul style="list-style-type: none"> Aligned Flex Alert templates in procedure with AWE Tool template, per Communications request. Minor formatting and grammar throughout. 	6/29/2017
8.0	Errata Change: version of last publish should reflect 8.0, but was noted as 8.1 in Version History only.	
8.1	Added Section 1.2.11 and 1.2.12 for Restricted Maintenance Operations Northern and Southern CA – Gas Supply Insufficiency added to AWE Tool. Noted Errata Change for version of last update in Version History. Minor formatting and grammar updates. Updated language of notices per updated templates (added California, replaced ISO with CAISO, and added websites references).	8/28/2018